



iGoLogic, Inc.
 46723 Fremont Blvd.
 Fremont, CA 94538
 Tel : 510-252-9388
 Fax : 510-252-9399

Model	EPIA CN13000G / (CN1000EG)	EPIA EN15000G / (EN1200EG)	EPIA EK10000G / (EK8000EG)	EPIA Nano N10000G / (N8000EG) / (N5000EG)	EPIA Nano NL10000G / (NL8000EG) / (NL5000EG)
Processor	VIA 1.3 GHz C7 / (VIA 1 GHz C7 Fanless)	VIA 1.5 GHz C7 / (VIA 1.2 GHz Eden Fanless)	1 GHz VIA Luke CoreFusion / (800 MHz VIA Luke CoreFusion)	1.00 GHz VIA Luke CoreFusion / (800 MHz VIA Luke CoreFusion Fanless) / (500 MHz VIA Luke CoreFusion Fanless)	1.00 GHz VIA Luke CoreFusion / (800 MHz VIA Luke CoreFusion Fanless) / (500 MHz VIA Luke CoreFusion Fanless)
Processor Core	Esther	Esther	Nehemiah C5P	Nehemiah C5P	Nehemiah C5P
Chipset	VIA CN700 & VT8237R	VIA CN700 & VT8237R	VT8237R	VIA CN400 & VIA VT8237	VIA CN400 & VIA VT8237
Memory	1 x DDR2 400/533 DIMM Slot Up to 1GB memory size	1 x DDR2 400/533 DIMM Slot Up to 1GB memory size	1 x DDR266/333/400 SODIMM Slot Up to 1GB memory size	1 x DDR266/333/400 SODIMM Slot Up to 1GB memory size	1 x DDR266/333/400 SODIMM Slot Up to 1GB memory size
IDE	2 x UltraDMA 133	2 x UltraDMA 133	1 x UltraDMA 133 (40 pin)	2 x UltraDMA 133/100/66	2 x UltraDMA 133/100/66
Serial ATA	2 x SATA Connectors	2 x SATA Connectors	2 x SATA Connectors	(secondary 2.0mm 44-pin header)	(secondary 2.0mm 44-pin header)
Floppy	--	--	--	1 x SATA Connector	1 x SATA Connector
USB	4 x Back Panel USB v2.0 2 x Onboard USB v2.0 via 1 pin header	4 x Back Panel USB v2.0 2 x Onboard USB v2.0 via 1 pin header	4 x Back Panel USB v2.0 4 x Onboard USB v2.0 via 2 pin headers	-- 2 x Back Panel USB v2.0	-- 8 x Onboard USB v2.0 via 1 pin header
Firewire (1394)	--	1 x Onboard 1394	--	4 x Onboard USB v2.0	--
VGA	Integrated VIA Unichrome Pro AGP Graphics with MPEG-2 accelerator	Integrated VIA Unichrome Pro AGP Graphics with MPEG-2 accelerator	Integrated VIA Unichrome Pro AGP Graphics with MPEG-2 accelerator	Integrated VIA Unichrome Pro AGP Graphics with MPEG-2/MPEG-4 Accelerator	Integrated S3 Graphics Unichrome Pro AGP Graphics with MPEG-2/MPEG-4 Accelerator
Shared Memory	64MB	64MB	64MB	64MB	64MB
DVI	--	--	--	--	--
TV Out	VT1625M	VT1625	--	VT1625	VT1625
S-Video Out	Yes	Yes	--	--	--
LVDS	--	Onboard LVDS Connector	Onboard LVDS Connector	Onboard LVDS Connector	Onboard LVDS Connector
Audio	VIA VT1618 8-channel AC'97 codec	VIA VT1618 6-channel AC'97 codec	VIA VT1618 8-channel AC'97 codec	VIA VT1617A 6-channel	VIA VT1617A 6-channel
LAN	1 x 10/100	1 x Gigabit	2 x 10/100	1 x 10/100	1 x 10/100
Keyboard / Mouse	1 x PS/2 keyboard port 1 x PS/2 mouse port	1 x PS/2 keyboard port 1 x PS/2 mouse port	1 x PS/2 keyboard port 1 x PS/2 mouse port	1 x PS/2 keyboard port 1 x PS/2 mouse port	1 x PS/2 keyboard port 1 x PS/2 mouse port
Serial Port	1 x Back Panel COM 1 x Onboard COM	1 x Back Panel COM 1 x Onboard COM	1 x Back Panel COM 3 x Onboard COM	--	--
Parallel Port	1 x Onboard LPT header	--	1 x Parallel port	--	--
PCI Slot	1 x PCI	1 x PCI	1 x PCI	1 x Mini-PCI	1 x Mini-PCI
Size	170mm x 170mm	170mm x 170mm	170mm x 170mm	120mm x 120mm	120mm x 120mm
Power Supply	ATX style	ATX style	ATX style	ATX style	ATX style
Accessories	ATA 133 flat cable (40 wire, 80 conductor, 3 connectors) Back plate Installation CD Quick installation guide	ATA 133 flat cable (40 wire, 80 conductor, 3 connectors) Back plate Installation CD Quick installation guide	ATA 133 flat cable (40 wire, 80 conductor, 3 connectors) Back plate Installation CD Quick installation guide	Heat sink with fan Heat paste for mounting heat sink ATX power adapter cable Header pin to PS/2 mouse and keyboard cable + screws Header pin to 2x USB cable + screws 40pin IDE cable Driver CD and quick start guide	Heat sink with fan Heat paste for mounting heat sink ATX power adapter cable Header pin to PS/2 mouse and keyboard cable + screws VGA Cable LAN Cable Header pin to 2x USB cable + screws 40pin IDE cable Driver CD and quick start guide